







1	SUHNER TYPE Order No.	31 BMA-SMA-50-1 / 1-9 UE 22645642
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 9 GHz: ≤ 1.04 + 0.02f	


5	SUHNER TYPE Order No.	34 BMA-SMA-50-2 / 1-- UE 22645650
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: ≤ 1.05 + 0.005f	


2	SUHNER TYPE Order No.	32 BMA-SMA-50-1 / 199 UE 22645643
BMA SMA	plug (m) plug (m)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 9 GHz: ≤ 1.067 + 0.017f 9 - 18 GHz: ≤ 1.22	

6	SUHNER TYPE Order No.	35 BMA-SMA-50-1 / 193 UE 22645647
BMA SMA	plug (m) plug (m)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: ≤ 1.05 + 0.005f	


3	SUHNER TYPE Order No.	33 BMA-SMA-50-1 / 199 UE 22645644
BMA SMA	plug (m) jack (f)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
VSWR:	DC - 18 GHz: ≤ 1.06 + 0.009f	

7	SUHNER TYPE Order No.	36 BMA-SMA-50-1 / 199 UE 22645651
BMA SMA	plug (m) jack (f)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 56	
VSWR:	DC - 18 GHz: ≤ 1.03 + 0.015f	

4	SUHNER TYPE Order No.	33 SMA-BMA-50-1 / 1-9 UE 22645645
SMA BMA	plug (m) jack (f)	
Packaging	single	
Material:		
SMA	stainless steel	
BMA	stainless steel	
VSWR:	DC - 18 GHz: ≤ 1.06 + 0.009f	


8	SUHNER TYPE Order No.	37 BMA-SMA-50-1 / 1-- UE 22645649
BMA SMA	jack (f) jack (f)	
Packaging	single	
Material:		
BMA	stainless steel	
SMA	stainless steel	
Mounting hole	ML 58	
VSWR:	DC - 9 GHz: ≤ 1.07 + 0.017f 9 - 18 GHz: ≤ 1.22	

9	SUHNER TYPE Order No.	31 BNC-MMCX-50-1 / 1-- UE 22645963
BNC MMCX	jack (f) jack (f)	
Packaging	single	
material BNC MMCX	brass/SUCO* brass/gold	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.04f$

13	SUHNER TYPE Order No.	33 MMCX-BNC-50-1 / 111 UE 22645966
MMCX BNC	plug (m) jack (f)	
Packaging	single	
material MMCX BNC	brass/gold brass/SUCO*	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.04f$

10	SUHNER TYPE Order No.	32 BNC-MMCX-50-1 / 1-- UE 22645959
BNC MMCX	plug (m) plug (m)	
Packaging	single	
material BNC MMCX	brass/SUCO* brass/gold	




VSWR: DC - 4 GHz: $\leq 1.03 + 0.05f$

14	SUHNER TYPE Order No.	35 BNC-MMCX-50-2 / 1 -- NE 23005885
BNC MMCX	plug (m) plug (m)	
Packaging	single	
Material: BNC MMCX	brass/SUCO* brass/gold	




VSWR: DC - 1 GHz: ≤ 1.03 ; 1 - 3 GHz: $\leq 0.935 + 0.095f$; 3 - 4 GHz: ≤ 1.22

11	SUHNER TYPE Order No.	33 BNC-MMCX-50-1 / 1-- NE 22652907
BNC MMCX	plug (m) jack (f)	
Packaging	single	
material BNC MMCX	brass/SUCO* brass/gold	




VSWR: DC - 4 GHz: $\leq 1.03 + 0.05f$

15	SUHNER TYPE Order No.	31 BNC-MCX-50-1 / 1-- UE 22543639
BNC MCX	jack (f) jack (f)	
Packaging	single	
material BNC MCX	brass/SUCO* brass/gold	




VSWR: DC - 2 GHz: $\leq 1.03 + 0.13f$
2 - 4 GHz: ≤ 1.29

12	SUHNER TYPE Order No.	33 BNC-MMCX-50-1 / 1-- UE 22645964
BNC MMCX	plug (m) jack (f)	
Packaging	single	
Material: BNC MMCX	brass/SUCO* brass/SUCO*	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.025f$

16	SUHNER TYPE Order No.	32 BNC-MCX-50-1 / 1-- UE 22543567
BNC MCX	plug (m) plug (m)	
Packaging	single	
Material: BNC MCX	brass/SUCO* CuBe/gold	




VSWR: DC - 2 GHz: $\leq 1.04 + 0.09f$
2 - 4 GHz: ≤ 1.22


17	SUHNER TYPE Order No.	33 BNC-MCX-50-1 / 1-- UE 22543829
BNC MCX	plug (m) jack (f)	
Packaging	single	
Material: BNC MCX	brass/SUCO* brass/gold	
VSWR:	DC - 4 GHz: ≤ 1.20	




21	SUHNER TYPE Order No.	34 BNC-MCX-50-2 / 133 UE 22644912
BNC MCX	jack (f) jack (f)	
Packaging	single	
Material: BNC MCX	brass/SUCO* brass/SUCO* Mounting hole ML 2	
VSWR:	DC - 4 GHz: ≤ 1.03 + 0.04f	




18	SUHNER TYPE Order No.	33 BNC-MCX-75-1 / 1-- NE 22649213
BNC MCX	plug (m) jack (f)	
Packaging	single	
Material: BNC MCX	brass/SUCO* brass/gold	




22	SUHNER TYPE Order No.	31 BNC-N-50-1 / 133 UE 22540549
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.22	




19	SUHNER TYPE Order No.	33 MCX-BNC-50-1 / 1-- UE 22543585
MCX BNC	plug (m) jack (f)	
Packaging	single	
Material: MCX BNC	CuBe/gold brass/SUCO*	
VSWR:	DC - 1 GHz: ≤ 1.04; 1 - 4 GHz: ≤ 1.22	




23	SUHNER TYPE Order No.	31 BNC-N-75-1 / 133 UE 22543640
BNC N	jack (f) jack (f)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	



20	SUHNER TYPE Order No.	33 MCX-BNC-75-1 / 1-- NE 22649211
MCX BNC	plug (m) jack (f)	
Packaging	single	
Material: MCX BNC	CuBe/gold brass/SUCO*	



24	SUHNER TYPE Order No.	32 BNC-N-50-1 / 133 UE 22540571
BNC N	plug (m) plug (m)	
Packaging	single	
Material: BNC N	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.06 + 0.4f	




25 SUHNER TYPE 32 BNC-N-75-1 / 133 UE
Order No. 22541022

BNC
N plug (m)
plug (m)

Packaging single

Material:
BNC brass/SUCO*
N brass/SUCO*




29 SUHNER TYPE 33 N-BNC-75-1 / 133 UE
Order No. 22542622

N BNC plug (m)
jack (f)

Packaging single

Material:
N brass/SUCO*
BNC brass/SUCO*




26 SUHNER TYPE 33 BNC-N-50-1 / 133 NE
Order No. 22540608

BNC N plug (m)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
N brass/SUCO*




VSWR: DC - 4 GHz: $\leq 1.04 + 0.025f$

30 SUHNER TYPE 34 BNC-N-50-1 / 133 UE
Order No. 22651055

BNC N jack (f)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
N brass/SUCO*
Mounting hole ML 12




VSWR: DC - 4 GHz: ≤ 1.22

27 SUHNER TYPE 33 BNC-N-75-1 / 133 UE
Order No. 22541034

BNC N plug (m)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
N brass/SUCO*




31 SUHNER TYPE 37 BNC-N-50-1 / 133 UE
Order No. 22649686

BNC N jack (f)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
N brass/SUCO*
Mounting hole ML 14




VSWR: DC - 4 GHz: ≤ 1.22

28 SUHNER TYPE 33 N-BNC-50-1 / 133 UE
Order No. 22542414

N BNC plug (m)
jack (f)

Packaging single

Material:
N brass/SUCO*
BNC brass/SUCO*




VSWR: DC - 4 GHz: ≤ 1.22

32 SUHNER TYPE 33 BNC-QLA-01-1 / 1-- NE
Order No. 22540624


BNC QLA 00 plug (m)
jack (f)

Packaging single


Material:
BNC brass/nickel
QLA 00 brass/nickel



33	SUHNER TYPE Order No.	33 QLA-BNC-01-1 / 1-- NE 22640029
QLA 00 BNC	plug (m) jack (f)	
Packaging	single	
Material: QLA 00 BNC	brass/nickel brass/SUCO*	




37	SUHNER TYPE Order No.	33 BNC-SMA-50-1 / 1-- UE 22540610
BNC SMA	plug (m) jack (f)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	




VSWR: DC - 4 GHz: $\leq 1.03 + 0.03f$

34	SUHNER TYPE Order No.	34 BNC-QLA-01-1 / 1-- UE 22640971
BNC QLA 00	jack (f) jack (f)	
Packaging	single	
Material: BNC QLA 00 Mounting hole	brass/SUCO* brass/SUCO* ML 2	




38	SUHNER TYPE Order No.	33 SMA-BNC-50-1 / 1-- NE 22640153
SMA BNC	plug (m) jack (f)	
Packaging	single	
Material: SMA BNC	CuBe/gold brass/SUCO*	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.037f$

35	SUHNER TYPE Order No.	31 BNC-SMA-50-1 / 1-- UE 22540551
BNC SMA	jack (f) jack (f)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	




VSWR: DC - 4 GHz: $\leq 1.06 - 0.04f$

39	SUHNER TYPE Order No.	34 BNC-SMA-50-2 / 1-- UE 22651028
BNC SMA	jack (f) jack (f)	
Packaging	single	
Material: BNC SMA Mounting hole	brass/SUCO* CuBe/gold ML 4	




VSWR: DC - 4 GHz: $\leq 1.06 + 0.03f$

36	SUHNER TYPE Order No.	32 BNC-SMA-50-1 / 1-- UE 22540572
BNC SMA	plug (m) plug (m)	
Packaging	single	
Material: BNC SMA	brass/SUCO* CuBe/gold	



VSWR: DC - 4 GHz: $\leq 1.03 + 0.03f$

40	SUHNER TYPE Order No.	31 BNC-SMB-50-2 / 1-- UE 22540553
BNC SMB	jack (f) jack (f)	
Packaging	single	
Material: BNC SMB	brass/SUCO* brass/gold	



VSWR: DC - 2 GHz: $\leq 1.03 + 0.095f$
2 - 4 GHz: ≤ 1.22


41 SUHNER TYPE 32 BNC-SMB-50-2 / 1-- UE
Order No. 22540574

BNC
SMB

plug (m)
plug (m)

Packaging single

Material:
BNC brass/SUCO*
SMB brass/gold



VSWR: DC - 4 GHz: ≤ 1.12


45 SUHNER TYPE 31 BNC-SMC-50-2 / 1-- NE
Order No. 22540555

BNC
SMC

jack (f)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
SMC brass/gold



VSWR: DC - 4 GHz: ≤ 1.22


42 SUHNER TYPE 33 BNC-SMB-50-2 / 1-- UE
Order No. 22540612

BNC
SMB

plug (m)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
SMB brass/gold



VSWR: DC - 4 GHz: $\leq 1.06 + 0.04f$


46 SUHNER TYPE 32 BNC-SMC-50-2 / 1-- NE
Order No. 22540576

BNC
SMC

plug (m)
plug (m)

Packaging single

Material:
BNC brass/SUCO*
SMC brass/gold



VSWR: DC - 4 GHz: ≤ 1.15


43 SUHNER TYPE 33 SMB-BNC-50-2 / 1-- UE
Order No. 22640396

SMB
BNC

plug (m)
jack (f)

Packaging single

Material:
SMB brass/gold
BNC brass/SUCO*



VSWR: DC - 4 GHz: $\leq 1.05 + 0.075f$


47 SUHNER TYPE 33 BNC-SMC-50-2 / 1-- NE
Order No. 22540616

BNC
SMC

plug (m)
jack (f)

Packaging single

Material:
BNC brass/SUCO*
SMC brass/gold



VSWR: DC - 4 GHz: ≤ 1.22

44 SUHNER TYPE 34 BNC-SMB-50-1 / 133 NH
Order No. 23001709


BNC
SMB

jack (f)
jack (f)

Packaging bulk 100 pcs.

Material:
BNC brass/SUCO*
SMB brass/SUCO*

Mounting hole ML 4



VSWR: DC - 2 GHz: ≤ 1.065
2 - 4 GHz: $\leq 0.8 + 0.13f$


48 SUHNER TYPE 33 SMC-BNC-50-2 / 1-- NE
Order No. 22640405

SMC
BNC


plug (m)
jack (f)


Packaging single


Material:
SMC brass/gold
BNC brass/SUCO*





VSWR: DC - 2 GHz: $\leq 1.03 + 0.095f$
2 - 4 GHz: ≥ 1.22


49	SUHNER TYPE Order No.	31 BNC-TNC-50-1 / 133 NE 22540559
BNC TNC	jack (f) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
		
VSWR:	DC - 4 GHz: ≤ 1.22	


53	SUHNER TYPE Order No.	33 TNC-BNC-75-1 / 133 UE 22640759
TNC BNC	plug (m) jack (f)	
Packaging	single	
Material: TNC BNC	brass/SUCO* brass/SUCO*	
		


50	SUHNER TYPE Order No.	32 BNC-TNC-50-1 / 133 NE 22540582
BNC TNC	plug (m) plug (m)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
		
VSWR:	DC - 4 GHz: ≤ 1.22	

54	SUHNER TYPE Order No.	37 BNC-TNC-50-1 / 133 UE 22540639
BNC TNC	jack (f) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
		
VSWR:	DC - 4 GHz: ≤ 1.22	

51	SUHNER TYPE Order No.	33 BNC-TNC-50-1 / 133 NE 22540614
BNC TNC	plug (m) jack (f)	
Packaging	single	
Material: BNC TNC	brass/SUCO* brass/SUCO*	
		
VSWR:	DC - 4 GHz: ≤ 1.22	

55	SUHNER TYPE Order No.	31 MMBX-SMA-50-1 / 111 NE 23004933
MMBX SMA	jack (f) jack (f)	
Packaging	single	
Material: MMBX SMA	brass/SUPR** CuBe/SUPR**	
		
VSWR:	DC - 1 GHz: ≤ 1.026; 1 - 2.5 GHz: ≤ 1.046 2.5 - 6 GHz: ≤ 1.083	

52	SUHNER TYPE Order No.	33 TNC-BNC-50-1 / 133 NE 22640631
TNC BNC	plug (m) jack (f)	
Packaging	single	
Material: TNC BNC	brass/SUCO* brass/SUCO*	
		
VSWR:	DC - 4 GHz: ≤ 1.22	

56	SUHNER TYPE Order No.	32 MMBX-SMA-50-1 / 119 NE 23004934
MMBX SMA	plug (m) plug (m)	
Packaging	single	
Material: MMBX SMA	CuBe/SUPR** CuBe/SUPR**	
		
VSWR:	DC - 1 GHz: ≤ 1.026; 1 - 2.5 GHz: ≤ 1.046 2.5 - 6 GHz: ≤ 1.083	

57	SUHNER TYPE Order No.	33 MMBX-SMA-50-1 / 111 NE 23004937
MMBX SMA	plug (m) jack (f)	
Packaging	single	
Material: MMBX SMA	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 1 GHz: ≤ 1.026; 1 - 2.5 GHz: ≤ 1.046 2.5 - 6 GHz: ≤ 1.083	

58	SUHNER TYPE Order No.	33 SMA-MMBX-50-1 / 119 NE 23004935
SMA MMBX	plug (m) jack (f)	
Packaging	single	
Material: SMA MMBX	CuBe/SUPR** brass/SUPR**	
VSWR:	DC - 1 GHz: ≤ 1.026; 1 - 2.5 GHz: ≤ 1.046 2.5 - 6 GHz: ≤ 1.083	

59	SUHNER TYPE Order No.	34 MMBX-TNC-50-1 / 1-3 NE 23014297
MMBX TNC	jack (f) jack (f)	
Packaging	single	
Material: MMBX TNC	brass/SUCO* brass/SUCO*	
VSWR:	DC - 5 GHz: ≤ 1.3	


60	SUHNER TYPE Order No.	31 MMCX-SMA-50-1 / 111 OE 22645961
MMCX SMA	jack (f) jack (f)	
Packaging	single	
Material: MMCX SMA	brass/gold CuBe/gold	
VSWR:	DC - 2.5 GHz: ≤ 1.10 2.5 - 6 GHz: ≤ 1.18	


61	SUHNER TYPE Order No.	31 MMCX-SMA-50-2 / 111 NE 22658201
MMCX SMA	jack (f) jack (f)	
Packaging	single	
Material: MMCX SMA	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 3.5 GHz: ≤ 1.07 3.5 - 6 GHz: ≤ 1.09	


62	SUHNER TYPE Order No.	32 MMCX-SMA-50-1 / 111 OE 22645967
MMCX SMA	plug (m) plug (m)	
Packaging	single	
Material: MMCX SMA	brass/gold CuBe/gold	
VSWR:	DC - 2.5 GHz: ≤ 1.10 2.5 - 6 GHz: ≤ 1.18	


63	SUHNER TYPE Order No.	33 MMCX-SMA-50-1 / 111 UE 22645970
MMCX SMA	plug (m) jack (f)	
Packaging	single	
Material: MMCX SMA	brass/gold CuBe/gold	
VSWR:	DC - 2.5 GHz: ≤ 1.10 2.5 - 6 GHz: ≤ 1.18	


64	SUHNER TYPE Order No.	33 SMA-MMCX-50-1 / 111 NE 22645969
SMA MMCX	plug (m) jack (f)	
Packaging	single	
Material: SMA MMCX	CuBe/gold brass/gold	
VSWR:	DC - 2.5 GHz: ≤ 1.10 2.5 - 6 GHz: ≤ 1.18	


65	SUHNER TYPE Order No.	33 SMA-MMCX-50-2 / 111 NE 22658204
SMA MMCX	plug (m) jack (f)	
Packaging	single	
Material: SMA MMCX	CuBe/SUPR** CuBe/SUPR**	
VSWR:	DC - 3.5 GHz: ≤ 1.065 3.5 - 6 GHz: ≤ 1.094	


66	SUHNER TYPE Order No.	31 MCX-N-50-1 / 1-- UE 22640172
MCX N	jack (f) jack (f)	
Packaging	single	
Material: MCX N	brass/gold brass/SUCO*	
VSWR:	DC - 6 GHz: ≤ 1.03 + 0.05f	


67	SUHNER TYPE Order No.	31 MCX-N-75-10 / 133 NE 22651488
MCX N	jack (f) jack (f)	
Packaging	single	
Material: MCX N	CuBe/SUCO* brass/SUCO*	
VSWR:	DC - 3 GHz: ≤ 1.07	

68	SUHNER TYPE Order No.	32 MCX-N-50-1 / 1-- UE 22543584
MCX N	plug (m) plug (m)	
Packaging	single	
Material: MCX N	CuBe/gold brass/SUCO*	
VSWR:	DC - 6 GHz: ≤ 1.03 + 0.05f	

69	SUHNER TYPE Order No.	33 MCX-N-50-1 / 1-- UE 22543586
MCX N	plug (m) jack (f)	
Packaging	single	
Material: MCX N	CuBe/gold brass/SUCO*	
VSWR:	DC - 6 GHz: ≤ 1.03 + 0.035f	

70	SUHNER TYPE Order No.	33 N-MCX-50-1 / 1-- UE 22543796
N MCX	plug (m) jack (f)	
Packaging	single	
Material: N MCX	brass/SUCO* brass/gold	
VSWR:	DC - 6 GHz: ≤ 1.03 + 0.03f	

71	SUHNER TYPE Order No.	33 N-MCX-75-1 / 1-- NE 22649214
N MCX	plug (m) jack (f)	
Packaging	single	
Material: N MCX	brass/SUCO* brass/gold	
VSWR:	DC - 3 GHz: ≤ 1.07	


72	SUHNER TYPE Order No.	34 MCX-N-50-1 / 133 UE 22646217
MCX N	jack (f) jack (f)	
Packaging	single	
Material: MCX N	brass/SUCO* brass/SUCO*	
Mounting hole:	ML 4	
VSWR:	DC - 6 GHz: ≤ 1.03 + 0.03f	

73 SUHNER TYPE 33 MCX-PC35-50-1 / 111 NE
Order No. 22651594

MCX
PC35 plug (m)
jack (f)

Packaging single

Material:
MCX CuBe/SUPR**
PC35 CuBe/SUPR**




VSWR: DC - 3.5 GHz: ≤ 1.065
3.5 - 6 GHz: ≤ 1.094

74 SUHNER TYPE 33 PC35-MCX-50-1 / 111 NE
Order No. 22651599

PC35
MCX plug (m)
jack (f)

Packaging single

Material:
PC35 CuBe/SUPR**
MCX CuBe/SUPR**




VSWR: DC - 3.5 GHz: ≤ 1.065
3.5 - 6 GHz: ≤ 1.094

75 SUHNER TYPE 31 MCX-SMA-50-1 / 111 NE
Order No. 22645485

MCX
SMA jack (f)
jack (f)

Packaging single

Material:
MCX brass/gold
SMA CuBe/gold




VSWR: DC - 6 GHz: ≤ 1.03 - 0.03f

76 SUHNER TYPE 32 MCX-SMA-50-1 / 111 NE
Order No. 22645486

MCX
SMA plug (m)
plug (m)

Packaging single

Material:
MCX brass/gold
SMA CuBe/gold




VSWR: DC - 6 GHz: ≤ 1.03 + 0.03f

77 SUHNER TYPE 33 MCX-SMA-50-1 / 111 UE
Order No. 22645487

MCX
SMA plug (m)
jack (f)

Packaging single

Material:
MCX CuBe/gold
SMA CuBe/gold




VSWR: DC - 6 GHz: ≤ 1.03 + 0.03f

78 SUHNER TYPE 33 SMA-MCX-50-1 / 111 NE
Order No. 22645488

SMA
MCX plug (m)
jack (f)

Packaging single

Material:
SMA CuBe/gold
MCX brass/gold




VSWR: DC - 6 GHz: ≤ 1.03 + 0.03f

79 SUHNER TYPE 34 MCX-TNC-50-1 / 133 UE
Order No. 22641905

MCX
TNC jack (f)
jack (f)

Packaging single

Material:
MCX brass/SUCO*
TNC brass/SUCO*
Mounting hole ML 2




VSWR: DC - 6 GHz: ≤ 1.07 + 0.07f

80 SUHNER TYPE 33 N-QLA-01-1 / 1-- NE
Order No. 22542431


N
QLA 00 plug (m)
jack (f)

Packaging single


Material:
N brass/SUCO*
QLA 00 brass/nickel




81 SUHNER TYPE 32 N-QN-50-1 / 133 NE Order No. 23033962

N QN	plug (m) plug (m)	
Packaging	single	
Material: N QN	brass/SUCO* brass/SUCO*	
VSWR:	DC - 4 GHz: ≤ 1.035; 4 - 8 GHz: ≤ 1.06 8 - 10 GHz: ≤ 1.22	


82 SUHNER TYPE 31 N-SMA-50-1 / 1-- UE Order No. 22542386

N SMA	jack (f) jack (f)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.015f	


83 SUHNER TYPE 32 N-SMA-50-1 / 11- NE Order No. 22542399

N SMA	plug (m) plug (m)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.017f	


84 SUHNER TYPE 33 N-SMA-50-1 / 113 UE Order No. 22542421

N SMA	plug (m) jack (f)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
VSWR:	DC - 12.4 Gz: ≤ 1.05 + 0.015f	


85 SUHNER TYPE 33 SMA-N-50-1 / 1-- UE Order No. 22640154

SMA N	plug (m) jack (f)	
Packaging	single	
Material: SMA N	CuBe/gold brass/SUCO*	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.015f	


86 SUHNER TYPE 34 N-SMA-50-1 / 193 UE Order No. 22642820

N SMA	jack (f) jack (f)	
Packaging	single	
Material: N SMA	stainless steel stainless steel	
Mounting hole	ML 12	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.017f	


87 SUHNER TYPE 37 N-SMA-50-1 / 1-- UE Order No. 22543458

N SMA	jack (f) jack (f)	
Packaging	single	
Material: N SMA	brass/SUCO* CuBe/gold	
Mounting hole	ML 13/14	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.015f	

88 SUHNER TYPE 39 SMA-N-50-1 / 1-- NE Order No. 22640156


SMA N	plug (m) jack (f)	
Packaging	single	
Material: SMA N	CuBe/gold brass/SUCO*	
Mounting hole	ML 13/14	
VSWR:	DC - 12.4 GHz: ≤ 1.05 + 0.015f	

97	SUHNER TYPE Order No.	33 N-SMC-50-1 / 1-- NE 22542423
N SMC	plug (m) jack (f)	
Packaging	single	
Material: N SMC	brass/SUCO* brass/SUCO*	




VSWR: DC - 2 GHz: ≤ 1.10 ; 2 - 4 GHz: ≤ 1.20
4 - 10 GHz: ≤ 1.40

98	SUHNER TYPE Order No.	33 SMC-N-50-1 / 1-- NE 22640406
SMC N	plug (m) jack (f)	
Packaging	single	
Material: SMC N	brass/gold brass/SUCO*	




VSWR: DC - 2 GHz: ≤ 1.10 ; 2 - 4 GHz: ≤ 1.20
4 - 10 GHz: ≤ 1.40

99	SUHNER TYPE Order No.	37 N-SMC-50-1 / 1-- UE 22641154
N SMC	jack (f) jack (f)	
Packaging	single	
Material: N SMC	brass/SUCO* brass/gold	
Mounting hole: ML 14		




VSWR: DC - 10 GHz: $\leq 1.06 + 0.084$

100	SUHNER TYPE Order No.	31 N-TNC-50-1 / 133 UE 22542392
N TNC	jack (f) jack (f)	
Packaging	single	
Material: N TNC	brass/SUCO* brass/SUCO*	




VSWR: DC - 7 GHz: $\leq 1.06 + 0.12f$
7 - 11 GHz: ≤ 1.90

101	SUHNER TYPE Order No.	32 N-TNC-50-1 / --- UE 22542406
N TNC	plug (m) plug (m)	
Packaging	single	
Material: N TNC	brass/SUCO* brass/SUCO*	




VSWR: DC - 11 GHz: $\leq 1.06 + 0.11f$

102	SUHNER TYPE Order No.	33 N-TNC-50-1 / 133 NE 22542427
N TNC	plug (m) jack (f)	
Packaging	single	
Material: N TNC	brass/SUCO* brass/SUCO*	




VSWR: DC - 11 GHz: $\leq 1.13 + 0.02f$

103	SUHNER TYPE Order No.	33 TNC-N-50-1 / 133 UE 22640637
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	brass/SUCO* brass/SUCO*	




VSWR: DC - 3 GHz: ≤ 1.05 ; 3 - 5.5 GHz: ≤ 1.18
5.5 - 11 GHz: ≤ 2.00

104	SUHNER TYPE Order No.	33 TNC-N-75-1 / 133 UE 22658811
TNC N	plug (m) jack (f)	
Packaging	single	
Material: TNC N	brass/SUCO* brass/SUCO*	




113	SUHNER TYPE Order No.	31 SMA-SMB-50-1 / 111 UE 22641728
SMA SMB	jack (f) jack (f)	
Packaging	single	
Material: SMA SMB	CuBe/gold brass/gold	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.04f$

114	SUHNER TYPE Order No.	33 SMA-SMB-50-1 / 111 NE 22658917
SMA SMB	plug (m) jack (f)	
Packaging	single	
Material: SMA SMB	brass/gold brass/gold	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.04f$
4 - 7 GHz: ≤ 1.21

115	SUHNER TYPE Order No.	33 SMB-SMA-50-1 / 111 UE 22641727
SMB SMA	plug (m) jack (f)	
Packaging	single	
Material: SMB SMA	brass/gold CuBe/gold	




VSWR: DC - 4 GHz: $\leq 1.05 + 0.04f$

116	SUHNER TYPE Order No.	31 SMA-TNC-50-1 / 1-- UE 22640941
SMA TNC	jack (f) jack (f)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	




VSWR: DC - 1 GHz: ≤ 1.05 ; 1 - 2 GHz: ≤ 1.10
2 - 6 GHz: ≤ 1.20 ; 6 - 10 GHz: ≤ 1.30

117	SUHNER TYPE Order No.	32 SMA-TNC-50-1 / 1-- UE 22640938
SMA TNC	plug (m) plug (m)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	




VSWR: DC - 2 GHz: ≤ 1.05 ; 2 - 4 GHz: ≤ 1.10
4 - 8 GHz: ≤ 1.20 ; 8 - 11 GHz: ≤ 1.30

118	SUHNER TYPE Order No.	33 SMA-TNC-50-1 / 1-- NE 22640939
SMA TNC	plug (m) jack (f)	
Packaging	single	
Material: SMA TNC	CuBe/gold brass/SUCO*	




VSWR: DC - 6 GHz: $\leq 1.03 + 0.05f$
6 - 11 GHz: ≤ 1.33

119	SUHNER TYPE Order No.	33 TNC-SMA-50-1 / 1-- UE 22640940
TNC SMA	plug (m) jack (f)	
Packaging	single	
Material: TNC SMA	brass/SUCO* CuBe/gold	



VSWR: DC - 2 GHz: ≤ 1.05 ; 2 - 4 GHz: ≤ 1.10
4 - 8 GHz: ≤ 1.20 ; 8 - 10 GHz: ≤ 1.30

120	SUHNER TYPE Order No.	33 SMB-TNC-50-2 / 1-- UE 22640400
SMB TNC	plug (m) jack (f)	
Packaging	single	
Material: SMB TNC	brass/gold brass/SUCO*	



VSWR: DC - 4 GHz: $\leq 1.1 + 0.065f$